Product datasheet

Specifications





current transformer tropicalised DIN mount 40 5 for cables d. 21

METSECT5CC004

Main

Range	PowerLogic
Product Name	СТ
Product Or Component Type	Current transformer
Secondary Current	5 A
Accuracy Class	Class 3 at 1 VA
[In] Rated Current	40 A

Complementary

Tropicalised for cable
40/5
2.4 kA
2.5 lth
5
< 720 V AC 50/60 Hz
3 kV
By screws Clip-on
Mounting plate DIN rail
Outside: 44 mm
Outside: 65 mm
Frame : 30 mm Total : 37 mm
21 mm
0.19 kg
3 kV
Class B
21 mm
With

Environment

Standards

VDE 0414 IEC 61869-2

Product Certifications	CE
Ip Degree Of Protection	IP20
Relative Humidity	095 %
Ambient Air Temperature For Operation	-2560 °C

Packing Units

-	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	5.600 cm
Package 1 Width	5.600 cm
Package 1 Length	8.600 cm
Package 1 Weight	188.000 g
Unit Type Of Package 2	S02
Number Of Units In Package 2	50
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	9.629 kg
Unit Type Of Package 3	P12
Number Of Units In Package 3	400
Package 3 Height	29.000 cm
Package 3 Width	80.000 cm
Package 3 Length	120.000 cm
Package 3 Weight	90.600 kg

Sustainability Screen

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Yes

Learn more about Green Premium >

Guide to assess a product's sustainability >



RoHS/REACh

Well-being performance



Rohs Exemption Information

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant with Exemptions
China Rohs Regulation	China RoHS declaration
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins