

## PowerLogic Split Core Current Transformer - Type HA, for cable -0250A / 5A

METSECT5HA025

#### Main

Range	PowerLogic	
Product Name	СТ	
Product Or Component Type	Current transformer	
Secondary Current	5 A	
Accuracy Class	Class 0.5 at 1 VA	
[In] Rated Current	250 A	

## Complementary

Current Transformer Type	Standard for cable Split core	
Current Transformer Ratio	250/5	
[Ith] Conventional Free Air Thermal Current	300 A	
Maximum Safety Factor	5	
Permissible Current	15000 A during 1 s	
[Ue] Rated Operational Voltage	< 720 V 50 Hz	
[Ui] Rated Insulation Voltage	3 kV	
Mounting Mode	Clip-on	
Width	Outside: 49 mm	
Height	Outside: 80.1 mm	
Depth	59 mm	
Diameter	18.4 mm inner:	
Electrical Insulation Class	nsulation Class Class E	
Cable Outer Diameter	Diameter 18.4 mm	
Connections - Terminals	Cable 2 cable(s) 0.51.5 mm² 0.5 m	

#### **Environment**

Standards	DIN EN 60044-1 DIN EN 61869-1 DIN EN 61869-2 VDE 0414
Ambient Air Temperature For Operation	-550 °C
Ambient Air Temperature For Storage	-2570 °C

# **Packing Units**

PCE
1
9.5 cm
6.5 cm
7.0 cm
332.0 g
S02
16
15.0 cm
30.0 cm
40.0 cm
5.53 kg

### Sustainability

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

### Well-being performance

<b>Ø</b>	Reach Free Of Svhc	
<b>Ø</b>	Toxic Heavy Metal Free	
<b>Ø</b>	Mercury Free	
<b>Ø</b>	Rohs Exemption Information	Yes
Read	ch Regulation	REACh Declaration
Eu R	Rohs Directive	Compliant EU RoHS Declaration
Chin	na Rohs Regulation	China RoHS declaration
Wee	е	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins